
## **AVR Two Drawer Filer**

Assembly Instructions - Please keep for future reference

617/3450

617/3467



#### **Dimensions**

Width - 40cm

Depth - 48cm

Height - 76cm

### Important - Please read these instructions fully before starting assembly

If you need help or have damaged or missing parts, call the Customer Helpline: 08456 400800



## Safety and Care Advice

#### Important - Please read these instructions fully before starting assembly

- Check you have all the components and tools listed on page 2 and 3.
- Remove all fittings from the plastic bags and separate them into their groups.
- Keep children and animals away from the work area, small parts could choke if swallowed.
- Make sure you have enough space to layout the parts before starting.

- Do not stand or put weight on the panels during assembly, this could cause damage.
- Assemble the item as close to its final position (in the same room) as possible.
- Assemble on a soft level surface to avoid damaging the unit or your floor.
- Parts of the assembly will be easier with 2 people.



 We do not recommend the use of power drill/driver for inserting screws,

as this could damage the unit.
Only use hand screwdrivers.

 Dispose of all packaging carefully and responsibly.


#### Care and maintenance

- Only clean using a damp cloth and mild detergent, do not use bleach or abrasive cleaners.
- From time to time check that there are no loose screws on this unit.
- This product should not be discarded with household waste.
   Take to your local authority waste disposal centre.


**Note:** If required the next page can be cut out and used as reference throughout the assembly. Keep this page with these instructions for future reference.

# Components - Panels

### Please check you have all the panels listed below




Right side (74 x 45cm)




Left side (74 x 45cm)




**3** Back (70.6 x 37.8cm)






**5** Drawer front x 2 (39.4 x 35.1cm)




6 Drawer bottom x 2 (34.5 x 32.8cm)




Back support (36.7 x 8cm)




**8** Bottom (36.7 x 44.8cm)



Drawer back x 2 (34.6 x 27cm)



10 Drawer right side x 2 (33.5 x 14cm)



11 Drawer left side x 2 (33.5 x 14cm)



## Components - Fittings

If you have damagde or missing components, call the **Customer Helpline: 08456 400800** 

### Please check you have all the fittings listed below

**Note:** The quantities below are the correct amount to complete the assembly. In some cases more fittings may be supplied than are required.

<b>A</b> ⊕	<b>B</b>	
57mm Screw x 8	Dowels x 16	Locking pin x 12
<b>D</b>		
Locking nuts x 12	12mm Screw x 20	Handle x 2
G (		
Handle screw x 4	Left side track x 2	Right side track x 2
<b>K</b> —		
Rail x 4	Plastic plug x 8	

#### Tools required



Phillips screwdriver (medium & large)

### Ruler - Use this ruler to help correctly identify the screws

### Step 1

#### Fitting the track


**a:** Use screws **a** to fix the left side track **a** on the left side panel **a**.

NOTE: Ensure the screws are located using the centre of the three locating holes.

The front part of the track should be close to the edge of the panel.

**b:** Slide the tracks to other side, then use screws **a** to fix the tracks.


Use the same method as in a:and b: to fix the right side tracks on the right side panel 1.



### Step 2

#### Fitting the side panels

a: Use screws to fix the right side panel 1 and left side panel 2 onto the bottom panel 8 and back support 7.



## Step 2 -continued

**b:** Slide back panel 3 into the unit.


## Step 3


#### Fitting the top panel


a: Screw locking pins **G** onto the top panel 4. Insert locking pins as far as shown.

**b:** Carefully locate the top panel 4 onto the unit.

b:







C:

a:

b:

### Step 3 -continued

c: Insert locking nuts into right side panel 1 and left side panel 2, then use a screwdriver to turn locking nuts clockwise to lock.

Use plastic plugs **1** to cover the screws.

### Step 4

#### Fitting the drawer

a: Insert dowels into drawer right side panel and drawer left sdie panel 11.

Screw locking pins into drawer back panel . Insert locking pins as far as shown.

Carefully insert the rails

Advisor, drawer right side


panel 10 and drawer left

side panel 11 onto drawer

back panel 9.

b: Insert locking nuts into drawer right side panel 10 and drawer left side panel 11, then use a screwdriver to turn locking nuts clockwise to lock.

Slide the drawer bottom panel 6 into the unit.




## Step 4 -continued

**C:** Screw locking pins **©** into drawer front panel **5**. Insert locking pins as far as shown.


C: 5

**d:** Carefully locate the drawer front panel 5 onto the unit.



e: Insert locking nuts into drawer right side panel 10 and drawer left side panel 11, then use a screwdriver to turn locking nuts clockwise to lock.

e:




### Step 4 -continued

f: Use handle screws 6 to fix the handle f onto the drawer front panel 5.


Use the same method as in a: - f: to fix the other drawer.


**g:** Use screws **(a)** to fix the drawers onto the tracks.

f:



g:






## Step 5

#### Finishing the unit

Carefully place the unit in the desired location.

Assembly is complete.



If you need help or have damaged or missing parts, call the Customer Helpline: 08456 400800