### Other electronic items, like TVs and mobile phones, are causing interference – try moving the Baby unit away from things like that.

- bought your baby monitor. 0808 100 6554\* This user guide is also available in other formats: large • the battery in the Parent unit isn't charged – try charging
- call our free Helpline. Our dedicated advisors are more likely to be able to help you than the retailer where you
- the units are too far apart try moving them closer together (but not closer than one metre)
- The units might be too close together. Make sure they're at least one metre apart, even when you're using the Talk button.

Why is my Parent unit beeping?

- The Parent unit beeps when:
- the Baby unit is turned off

it for 12 hours

What should I do?

- **3** both units are turned on 4 the Parent unit isn't too far from the Baby unit (large
- obstructions or other electrical devices might affect the

5 unplugging the power cables, waiting about 15 seconds,

My Parent/Baby unit is making a high-pitched noise.

and then plugging them back in can help.

- is fully charged (for 12 hours)

- signal between the Parent and Baby unit).

- wall socket 2 the Baby unit is plugged in and the Parent unit battery
- 1 power cables are plugged in and switched on at the
- Check that:

- Troubleshooting
- My Parent/Baby unit isn't working. What should I do?

and affect how they link to each other.

Separation of the range?

Parent unit on.

teedback sounds.

.no ti dotiwa

they are now ready to use.

indoors. Thick walls and doors reduce the units' range

I he maximum range between your Parent and Baby

units is about 250 metres outdoors and about 50 metres

The Parent and Baby unit are automatically linked so

Press the 👅 button and hold for 2 seconds to turn the

from the Baby unit. Any closer and you might get audio

Before you do, move the Parent unit at least one metre

Observe the Parent unit has charged for 12 hours you can

## Why is the Parent unit not making any sounds even • the Parent unit might not be fully charged - make sure

it's charged (for 12 hours).

Need some help?

Frequently asked questions are available online.

If you cannot find the answer to your question online,

print, Braille and audio CD. Call the helpline for a copy.

L bt.com/producthelp

\* Calls made from within the UK mainland network are free.

Mobile and international call costs may vary.

•

the speaker volume might be switched off.

# though there's noise coming from my baby's room?

# General information

### Guarantee

### Your Video Baby Monitor 3000 is guaranteed for a period of 24 months from the date of purchase Subject to the terms listed below, the guarantee will provide for the repair of, or at BT's or its agent's discretion the option to replace the Video Baby Monitor 3000, or any component thereof, which

The conditions of this guarantee are:

• The guarantee shall only apply to

• Proof of purchase is required.

guarantee period.

agent as instructed.

approved agents.

statutory rights.

**(€ Å** 

defects that occur within the 24 month

• The equipment is returned to BT or its

This guarantee does not cover any faults

or defects caused by accidents, misuse,

fair wear and tear, neglect, tampering

with the equipment, or any attempt at

This guarantee does not affect your

© British Telecommunications plc 2017.

go to bt.com/producthelp

adjustment or repair other than through

To find out what to do, if your monitor is

in or outside of the 24 month guarantee.

# is identified as faulty or below standard. or as a result of inferior workmanship or materials. Products over 28 days old from the date of purchase may be replaced with a refurbished or repaired product.

### The symbol shown here and on th product means that the product is classed as electrical or electronic equipment, so DO NOT put it in your normal rubbish bin.

# How to recycle your equipment

It's all part of the Waste Electrical and

Electronic Equipment (WEEE) Directive to

recycle products in the best way - to be

kinder to the planet, get rid of dangerous

things more safely and bury less rubbish

You should contact your retailer or

supplier for advice on how to dispose

of this product in an environmentally

**Radio Equipment Directive** 

**Declaration of Conformity** 

This device has been evaluated for

and shown compliant with European

with a minimum distance of 16mm

The item code for both power supply

The full text of the FLI declaration of

Frequency range 2415.375 -

Max power

Registered Office: 81 Newgate Street, London EC1A 7AJ. Registered in England No. 1800000 Designed and produced by The Art & Design Partnership (ADP). Printed in China / Issue 5 / ADP12-17

conformity is available at the following

internet address: bt.com/producthelp

Radio transmission information

2471.625MHz

89.54mW (19.52dBm)

units is 089009 (BLJ06W050060P1-B).

between the unit and your body.

Guidelines when installed and operated

Hereby, British Telecommunications plc

declares that the radio equipment type BT

Video Baby Monitor 3000 (088304) is in

compliance with Directive 2014/53/EU.

in the around.

friendly way.

# dn tes pritter

mains power socket and switch the socket on. 🕒 Plug the cable into the Parent unit, then plug it into the



## Leave to charge for 12 hours.

# qiT

used it for a long time, it'll take 12 hours to fully charge. The first time you use the Parent unit, or if you haven't

short time. minutes to charge enough for you to use it for a When the battery gets very low, it'll take about 30

turn it off while it's charging. To charge the Parent unit in the shortest amount of time,



mains power socket and switch the socket on.

Blace the Baby unit near a power socket in the room

the time. It should also be at least one metre away from

where you're going to be monitoring your baby most of



# .no to turn it on.

## qiT

Nonu papy.

extra length and securing it. Keep the power cord out of baby's reach by looping any



# Video Baby Monitor 3000 **User Guide**



# Welcome

tor your baby's every breath, gurgle and wriggle. be able to relax knowing you can watch and listen Thanks for buying a BT Baby Monitor. You'll soon

or give us a call on 0808 100 6554\*. opposite. If you need any help, go to bt.com/producthelp But first things first. To get set up, just follow the steps

### Important safety notices

- .noisivisquas flube It isn't a substitute for responsible and proper 1. Your baby monitor is designed as just an aid.
- reach at least one metre away. 2. Make sure all cables and units are out of your baby's
- inside the cot, bed or playpen. 3. Never cover either unit, put them in moist places or
- plugs match the local power output. 4. If you travel abroad, check the voltage on your unit's
- get in touch with our helpdesk. Do not take the product apart. If you need repairs,

# Using the Parent unit



There are 5 lullabies to choose from or you can play all 5 in sequence.

- 1. Press Menu, d is displayed, press OK
- 2. Press ▲ or w to choose the lullaby 1–5 or press 3 to play all five, then press or .
- 3. Press or to select the volume from 1-3 and press or to save.
- 4. To stop the lullaby playing, select ⊘.

## Talk to your baby

To give your baby some words of comfort, press and hold down tak on the Parent unit and speak into the Parent unit's microphone. The  $\frac{0}{2}$  icon will be displayed at the bottom right corner. Release the button when you've finished speaking.

## € Zoom in and out

- 1. Press  $\underline{\mathsf{Mem}}$ , then press  $\underline{\checkmark}$  to display P and press  $\underline{\mathsf{OK}}$ .
- 2. Press or to select the zoom level (X1 or X2), then press or to save.
- 3. Press Menu to return to the main monitoring screen.
- 4. Whilst in X2 mode, press , , , , , , , , , to move the image.

battery low.

after the parent unit

is turned off).

when you're in the menu.

To adjust the volume or screen brightness when in X2 zoom mode, press Menu and select the () or () option and press ().

# Get to know your Baby unit



**Power socket** 

Stand

Lift and twist.

1. 2. 3.

1.

### Set a reminder

You can set an alert to remind you of something you need to do, for example when your baby's next feed is due. You can set it for 2, 4 or 6 hours.

1. Press Menu, then press v to display 2 and press K

2. Press or to select the reminder time (2H, 4H or 6H),

then press or to save. The 🕐 will be displayed on the top right of the screen.

3. To cancel the alert, select  $\oslash$ .

### Det the screen to turn on and off automatically

You can set the screen to turn on by pressing any button. On this setting, the screen will turn off automatically when no button is pressed during 1, 3 or 5 minutes.

1. Press Menu, then press v to display DID and press or

Press and to select 1, 3 or 5 minutes and press or.
To turn the screen back on at any time, press any button. If you want to set the screen on all the time, set the screen setting in to off O.

### (B) Turn sound activated screen mode on or off

When set to On, the screen will turn on if noise is detected from the Baby unit. If it's set to Off, the screen will stay off even if noise is detected. To use this feature, you need to set the standby mode first to 1, 3 or 5 minutes as described above.

1. Press Menu, then press v to display (B) and press or .

Press ▲ and ▲ to select ✔ (for On) or ★ (for Off) and press <sup>OK</sup>.
To turn the screen back on at any time, press the .

### Temperature sensor

The reading from the temperature sensor will be displayed at the top of the Parent unit screen.

To change the temperature display from C to F:

1. Press Menu, then press v to display i and press or.

2. Press or to select °C or °F, then press or

### Other screen icon descriptions

Till Signal strength

D Baby unit switched on

**Q1** Camera identification number e.g. Camera 1

Sound on

🔆 Mute

Battery status (Full battery shown,

scrolling when charging)

# Using the Baby unit

Off G-On Turn on and off

1. Slide the Off Ce On button on the side of the unit up to turn On and press down to turn Off.

### **(** Night vision

So that you can see your baby at night, the Baby unit automatically uses the light from its infrared LED lights to capture images in a dark room. Because of that, it can only show images in black and white. The  $\pounds$  icon will be displayed at the top of the screen.